

DUST MONKEY ECOFIL

WWW.DUSTMONKEY.NET

SPECIFICATIONS

Cleaning motor vehicle and filtering cartridges in general air filters without the proper tools is a difficult and unhealthy operation, leading to the dispersion of large quantities of dust in the work environment. In the majority of cases such difficulties mean filters tend to be replaced when they could easily be reused, with significant savings in terms of costs. Dust Monkey offers its the Ecofil filter, which allows for the rapid, economic and clean restoration of air filters. Given the simplicity of cleaning filters with Ecofil, this process can be

frequently carried out, thus restoring the maximum possible filtering efficiency. The Ecofil unit comprises a cleaning chamber, with a hatch for installing cartridges, and a ducting connection; the chamber is mounted on 4 legs and connected to a filter (optional) that depresses the chamber, returning the filtered air to the environment. Ecofil comes in two versions: A and C) manual control, B) automatic control. In the manual control version, the cartridge is introduced by means of the hatch, lowering the cartridge cap



and switching on the aspirator group. In the automatic control version, once the cartridge has been introduced, simply press the cycle start button on the panel, after which the entire process is carried out automatically.

FEATURES

- * The filter allows for the rapid, economic and clean restoration of air filters!
- * Cleans filters so that they may be reused, lowering costs associated with buying replacement filters.
- * Both automatic and manual versions available!

OPTIONS

- * Filters available
- * Manual or automatic cleaning process
- * Nozzle extension compressed air gun

DIMENSIONS, ETC.

Dust Monkey products are manufactured in metric sizes but described here and on the web site in their closest English equivalent. Representative sizes and dimensions are described here. Custom sizes and materials are available.

Diameters:
63 mm: 2.5 inches
75 mm: 3 inches
100 mm: 4 inches
125 mm: 5 inches
160 mm: 6 inches
200 mm: 8 inches

Lengths:
1.5m: 5 feet
2.0m: 6 feet
3.0m: 10 feet
4.0m: 13 feet
5.0m: 16 feet
6.0m: 20 feet
7.0m: 23 feet
8.0m: 26 feet
9.0m: 30 feet

WWW.DUSTMONKEY.NET

Komodo Enterprises, Inc. DBA
Dust Monkey
2620 S. Maryland Pkwy
Suite 14, Box 863
Las Vegas, NV 89109

California Office
8915 Research Dr.
Irvine CA, 92618

Tel: 949.341.0314
Fax: 949.341.0315

E-mail: info@dustmonkey.net



*Tough, Durable,
Rugged, Reliable,
Stout Construction*

Visit all our web sites:
WWW.DUSTMONKEY.NET
WWW.DUCTMONKEY.NET
WWW.MONKEYARMS.COM



*Experts in Dust, and
Fume Control.*

MODELS AVAILABLE

ECOFIL	POWER (HP)	FILTERING SURFACE (SQ FT)	MAX DELIVERY (CFM)	AVERAGE SOUND LEVEL dB(A)	Ø OF INTAKE OPENING (IN)	WEIGHT (LB)
100	2	48.5	529	64	4	375
140	3	96.9	882	66	5.69	441
160	3	96.9	1059	66	6.37	441
200	5.5	193.8	1764	69	8	705

WWW.DUSTMONKEY.NET

TERMS AND CONDITIONS

PAYMENTS AND TERMS

Prices quoted are good for 30 days unless otherwise noted. Dust Monkey accepts cash, check, wire transfer, or credit cards. All prices are quote in US Dollars, unless otherwise noted. All sales are final. All freight is FOB, Las Vegas, Nevada unless otherwise noted. All goods remain the property of Dust Monkey until paid in full. Payment is due at time of order unless credit has been granted. All past due accounts accrue a service fee of 3% per month. Dust Monkey is a DBA of Komodo Enterprises, Inc., a Nevada Corporation.

PRIVACY STATEMENT

Komodo Enterprises Inc. respects your privacy and will not divulge your contact information to any third party organization or entity without your express permission. In addition, our web sites gather no unauthorized information from your computer during your visit with us. All phone calls to Dust Monkey may be monitored or recorded.

ACCURACY

Dust Monkey assumes no responsibility for errors or omissions in this web site or documents which are referenced by or linked to this site. This site could include technical or other inaccuracies. Changes are periodically added to the information, and Dust Monkey may change the products or services described at any time. Contact Customer Service for further information before relying on any information contained herein. The information provided on this site, including text, images, and links, are provided "AS IS" by Dust Monkey solely as a convenience to its visitors. This information is without any warranties, express or implied, including but not limited to warranties of merchantability, fitness for a particular purpose or non-infringement.

WARRANTY & INDEMNITY

Dust Monkey warrants products it manufactures for a period of 90 days to the original purchaser from the date of purchase. Items not manufactured by Dust Monkey are limited to their own manufacturer's warranties. This warranty does not apply to defects due directly or indirectly to misuse, negligence, accidents, abuse, repairs, or alterations or lack of maintenance. This is Dust Monkey's sole written warranty and any and all warranties that may be implied by law, including any merchantability or fitness, for any particular purpose, are hereby limited to the duration of this written warranty. Dust Monkey does not warrant or represent that the merchandise complies with the provisions of any law or acts. In no event shall Dust Monkey liability under this warranty exceed the purchase price paid for the product. Both parties agree to binding arbitration in Las Vegas, Nevada. Dust Monkey shall in no event be liable for death, injuries to persons or property or for incidental, and contingent, special, or consequential damages arising from the use of our products. Dust Monkey warrants products only for the specific use expressly agreed to at time of purchase by Dust Monkey in writing. Motors should only be started and stopped up to 4 - 10 times per hour. Starting motors more frequently can cause heat build up and can cause the motor overload to trip or cause motor damage. In general, motors should be started and stopped as little as possible for maximum lifespan and best economy (electrical use). *Note: Motors should be protected from extreme weather to prolong motor life. All claims, including claims covered under the limited warranty, are subject to inspection and investigation before Buyer's claim is settled. Any parts returned for warranty or repair will not be accepted without an RMA number and must be shipped pre-paid. Contact Customer Service with the original bill of sale to obtain an RMA number.